


KEY FEATURES

- 3.3V device with up to four independently controlled VDDO (1.8V - 3.3V)
- Two of four integrated PLLs support spread spectrum generation for EMI reduction
- Integrated VCXO
- Output frequency range: 4.9 kHz to 500 MHz
– 1.8 - 3.3 V LVTTTL/ LVCMOS
– LVPECL, LVDS and HCSL
- Programmable loop bandwidth
- Programmable slew rate control,
- Redundant clock inputs with glitchless auto and manual switchover options
- Small 4x4mm and 5x5mm QFN and TSSOP packages

VERSACLOCK III SOFTWARE OPTIMIZES CONFIGURATIONS

- Automatic analysis and adjustment of spread spectrum, loop bandwidths and outputs
- Provides clock to pin locking and multi-register configuration
- Bit-level manipulation
- Direct software interface with VersaClock III evaluation board
- Free download from www.idt.com/go/versaclock3



IDT VersaClock products save cost, reduce board space and greatly increase versatility in consumer, data communications, telecommunications and networking applications.

Multi purpose clock provides many solutions


VersaClock® products allow designers to save board space and cost by replacing crystals, oscillators and buffers with a single timing device. Exceptional versatility and configurability allow for maximum freedom in the design process.

There are four internal PLLs, each individually programmable, allowing for up to seven unique frequencies. These frequencies are generated from a single reference clock, which can come from one of two redundant clock inputs. A glitchless automatic or manual switchover function allows the redundant clock to be selected during normal operation.

VersaClock devices are highly configurable and can be programmed through the use of the I²C interface. The programming interface enables the device to be programmed when it is in normal operation. An internal EEPROM allows the user to save and restore the configuration of the device without having to reprogram it on power-up.

VersaClock products from IDT provide an almost universal solution for a variety of high performance clock applications.

VERSACLOCK III EVALUATION BOARD



- Direct USB interface
- Configure device using VersaClock software
- Crystal or SMA clock input
- On board programmable LDOs for optimized VDDO settings
- Matched differential output traces
- Multiple daughtercards with sockets available to program additional devices

FEATURES

- Four internal PLLs
- Optional integrated VCXO
- Internal non-volatile EEPROM
- Each PLL has a 7-bit reference divider and a 12-bit feedback divider
- Fast (400 kHz) mode I²C serial interface for device configuration
- 8-bit output divider clocks
- Output frequency range: 4.9 kHz to 500 MHz
- Programmable loop bandwidth settings
- Input clock frequency range: 1 MHz to 200 MHz
- Programmable output inversion to reduce jitter
- Reference crystal input with programmable linear load capacitance
 - Crystal frequency range: 8 to 50 MHz
- I / O Standards:
 - Outputs – 1.8/2.5/3.3 V LVTTTL / LVCMOS (device dependent)
 - Outputs – LVPECL, LVDS and HCSL
 - Inputs – LVTTTL / LVCMOS
- Two PLLs support spread spectrum generation
- Redundant clock inputs with glitch-less auto switchover
- Fractional divide capability on one PLL
- -40 to +85°C industrial temperature operation

VersaClock III Parts

XO	Package	Output No.	Output Type	VDDO
5V49EE901	TSSOP28, QFN32 (5x5mm)	9	LVTTTL, LVPECL, LVDS, HCSL	No
5V49EE902	QFN32 (5x5mm)	9	LVTTTL, LVPECL, LVDS, HCSL	Yes - 4
5V49EE903	TSSOP28, QFN32 (5x5mm)	9	LVTTTL	No
5V49EE904	QFN32 (5x5mm)	9	LVTTTL	Yes - 4
5V49EE701	QFN28 (4x4mm)	7	LVTTTL, LVPECL, LVDS, HCSL	No
5V49EE702	QFN28 (4x4mm)	7	LVTTTL, LVPECL, LVDS, HCSL	Yes - 3
5V49EE703	QFN28 (4x4mm)	7	LVTTTL	No
5V49EE704	QFN28 (4x4mm)	7	LVTTTL	Yes - 3
5V49EE501	QFN24 (4x4mm)	5	LVTTTL, LVPECL, LVDS, HCSL	No
5V49EE502	QFN24 (4x4mm)	5	LVTTTL, LVPECL, LVDS, HCSL	Yes - 2
5V49EE503	QFN24 (4x4mm)	5	LVTTTL	No
5V49EE504	QFN24 (4x4mm)	5	LVTTTL	Yes - 2
VCXO	Package	Output No	Output Type	VDDO
5V19EE901	TSSOP28, QFN32 (5x5mm)	9	LVTTTL, LVPECL, LVDS, HCSL	No
5V19EE902	QFN32 (5x5mm)	9	LVTTTL, LVPECL, LVDS, HCSL	Yes - 4
5V19EE903	TSSOP28, QFN32 (5x5mm)	9	LVTTTL	No
5V19EE904	QFN32 (5x5mm)	9	LVTTTL	Yes - 4
5V19EE603	QFN28 (4x4mm)	6	LVTTTL	No
5V19EE604	QFN28 (4x4mm)	6	LVTTTL	Yes - 3
5V19EE403	QFN24 (4x4mm)	4	LVTTTL	No
5V19EE404	QFN24 (4x4mm)	4	LVTTTL	Yes - 2

Discover what IDT know-how can do for you:
www.IDT.com/go/versaclock3

DISCLAIMER Integrated Device Technology, Inc. (IDT) and its subsidiaries reserve the right to modify the products and/or specifications described herein at any time and at IDT's sole discretion. All information in this document, including descriptions of product features and performance, is subject to change without notice. Performance specifications and the operating parameters of the described products are determined in the independent state and are not guaranteed to perform the same way when installed in customer products. The information contained herein is provided without representation or warranty of any kind, whether express or implied, including, but not limited to, the suitability of IDT's products for any particular purpose, an implied warranty of merchantability, or non-infringement of the intellectual property rights of others. This document is presented only as a guide and does not convey any license under intellectual property rights of IDT or any third parties. IDT's products are not intended for use in life support systems or similar devices where the failure or malfunction of an IDT product can be reasonably expected to significantly affect the health or safety of users. Anyone using an IDT product in such a manner does so at their own risk, absent an express, written agreement by IDT.

Integrated Device Technology, IDT and the IDT logo are registered trademarks of IDT. Other trademarks and service marks used herein, including protected names, logos and designs, are the property of IDT or their respective third party owners. © Copyright 2011. All rights reserved.

PB_VERSACLOCK_III_REV0611